

Symbols for Legacy Computing

Range: 1FB00–1FBFF

This chart contains an excerpt from the character code tables and list of character names for *The Unicode Standard, Version 18.0*

This file will not be updated with errata, or when additional characters are assigned to the Unicode Standard.

See <https://www.unicode.org/errata/> for an up-to-date list of errata.

See <https://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <https://www.unicode.org/charts/PDF/Unicode-18.0/> for charts showing only the characters added in Unicode 18.0. See <https://www.unicode.org/Public/18.0.0/charts/> for a complete set of character code charts for Unicode 18.0. See <https://www.unicode.org/Public/18.0.0/charts/About.html#Conventions> for conventions used in these code charts, and other general information.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 18.0 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 18.0, online at:

<https://www.unicode.org/versions/Unicode18.0.0/>

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts.

See <https://www.unicode.org/charts/fonts.html> for a list.

Terms of Use

© 1991–2026 Unicode, Inc. This publication is protected by copyright, and permission must be obtained from Unicode, Inc. prior to any reproduction, modification, or other use not permitted by the Terms of Use (<https://www.unicode.org/copyright.html>). Specifically, you may make copies of this publication and may annotate and translate it solely for personal or internal business purposes and not for public distribution, provided that any such permitted copies and modifications fully reproduce all copyright and other legal notices contained in the original. You may not make copies of or modifications to this publication for public distribution, or incorporate it in whole or in part into any product or publication without the express written permission of Unicode.

The Unicode Consortium specifically grants ISO a license to produce such code charts with their associated character names list to show the repertoire of characters for that standard, as a normatively referenced, integral part of that standard.

Unicode uses most fonts under restricted license from the original font owner. You may not extract, copy, modify, or distribute fonts or font data from any Unicode Products, including this publication, without license from the font owner.

Use of all Unicode Products, including this publication, is governed by the Unicode Terms of Use (<https://www.unicode.org/copyright.html>). The authors, contributors, and publishers have taken care in the preparation of this publication, but make no express or implied representation or warranty of any kind and assume no responsibility or liability for errors or omissions or for consequential or incidental damages that may arise therefrom. This publication is provided “AS-IS” without charge as a convenience to users.

Unicode and the Unicode Logo are registered trademarks of Unicode, Inc., in the United States and other countries.

	1FB0	1FB1	1FB2	1FB3	1FB4	1FB5	1FB6	1FB7	1FB8	1FB9	1FBA	1FBB	1FBC	1FBD	1FBE	1BF0
0																
1																
2																
3																
4																
5																
6																
7																
8																
9																
A																
B																
C																
D																
E																
F																

Block mosaic terminal graphic characters

The term "sextant" refers to block mosaics divided into six parts.

1FB00	■	BLOCK SEXTANT-1
1FB01	■	BLOCK SEXTANT-2
1FB02	■	BLOCK SEXTANT-12
		• upper one third block
1FB03	■	BLOCK SEXTANT-3
1FB04	■	BLOCK SEXTANT-13
1FB05	■	BLOCK SEXTANT-23
1FB06	■	BLOCK SEXTANT-123
1FB07	■	BLOCK SEXTANT-4
1FB08	■	BLOCK SEXTANT-14
1FB09	■	BLOCK SEXTANT-24
1FB0A	■	BLOCK SEXTANT-124
1FB0B	■	BLOCK SEXTANT-34
		• middle one third block
1FB0C	■	BLOCK SEXTANT-134
1FB0D	■	BLOCK SEXTANT-234
1FB0E	■	BLOCK SEXTANT-1234
		• upper two thirds block
1FB0F	■	BLOCK SEXTANT-5
1FB10	■	BLOCK SEXTANT-15
1FB11	■	BLOCK SEXTANT-25
1FB12	■	BLOCK SEXTANT-125
1FB13	■	BLOCK SEXTANT-35
1FB14	■	BLOCK SEXTANT-235
1FB15	■	BLOCK SEXTANT-1235
1FB16	■	BLOCK SEXTANT-45
1FB17	■	BLOCK SEXTANT-145
1FB18	■	BLOCK SEXTANT-245
1FB19	■	BLOCK SEXTANT-1245
1FB1A	■	BLOCK SEXTANT-345
1FB1B	■	BLOCK SEXTANT-1345
1FB1C	■	BLOCK SEXTANT-2345
1FB1D	■	BLOCK SEXTANT-12345
1FB1E	■	BLOCK SEXTANT-6
1FB1F	■	BLOCK SEXTANT-16
1FB20	■	BLOCK SEXTANT-26
1FB21	■	BLOCK SEXTANT-126
1FB22	■	BLOCK SEXTANT-36
1FB23	■	BLOCK SEXTANT-136
1FB24	■	BLOCK SEXTANT-236
1FB25	■	BLOCK SEXTANT-1236
1FB26	■	BLOCK SEXTANT-46
1FB27	■	BLOCK SEXTANT-146
1FB28	■	BLOCK SEXTANT-246
1FB29	■	BLOCK SEXTANT-1246
1FB2A	■	BLOCK SEXTANT-346
1FB2B	■	BLOCK SEXTANT-1346
1FB2C	■	BLOCK SEXTANT-2346
1FB2D	■	BLOCK SEXTANT-12346
		• lower one third block
1FB2E	■	BLOCK SEXTANT-156
1FB2F	■	BLOCK SEXTANT-256
1FB30	■	BLOCK SEXTANT-1256
		• upper and lower one third block
1FB31	■	BLOCK SEXTANT-356
1FB32	■	BLOCK SEXTANT-1356
1FB33	■	BLOCK SEXTANT-2356
1FB34	■	BLOCK SEXTANT-12356

1FB35	■	BLOCK SEXTANT-456
1FB36	■	BLOCK SEXTANT-1456
1FB37	■	BLOCK SEXTANT-2456
1FB38	■	BLOCK SEXTANT-12456
1FB39	■	BLOCK SEXTANT-3456
		• lower two thirds block
1FB3A	■	BLOCK SEXTANT-13456
1FB3B	■	BLOCK SEXTANT-23456

Smooth mosaic terminal graphic characters

1FB3C	▲	LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB3D	▲	LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB3E	▲	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB3F	▲	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB40	▲	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB41	▲	LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE
1FB42	▲	LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB43	▲	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB44	▲	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB45	▲	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB46	▲	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB47	▲	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB48	▲	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB49	▲	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB4A	▲	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB4B	▲	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB4C	▲	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB4D	▲	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB4E	▲	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB4F	▲	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB50	▲	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB51	▲	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB52	▲	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB53	▲	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB54	▲	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB55	▲	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB56	▲	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB57	▲	UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE

1FB58	➤	UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB59	➤	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB5A	➤	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB5B	➤	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB5C	➤	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB5D	➤	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB5E	➤	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB5F	➤	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB60	➤	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB61	➤	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB62	➤	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB63	➤	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB64	➤	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB65	➤	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB66	➤	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB67	➤	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB68	➤	UPPER AND RIGHT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB69	➤	LEFT AND LOWER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6A	➤	UPPER AND LEFT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB6B	➤	LEFT AND UPPER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6C	➤	LEFT TRIANGULAR ONE QUARTER BLOCK
1FB6D	➤	UPPER TRIANGULAR ONE QUARTER BLOCK
1FB6E	➤	RIGHT TRIANGULAR ONE QUARTER BLOCK
1FB6F	➤	LOWER TRIANGULAR ONE QUARTER BLOCK

Block elements

1FB70		VERTICAL ONE EIGHTH BLOCK-2 → 258F left one eighth block
1FB71		VERTICAL ONE EIGHTH BLOCK-3
1FB72		VERTICAL ONE EIGHTH BLOCK-4
1FB73		VERTICAL ONE EIGHTH BLOCK-5
1FB74		VERTICAL ONE EIGHTH BLOCK-6
1FB75		VERTICAL ONE EIGHTH BLOCK-7 → 2595 right one eighth block
1FB76	—	HORIZONTAL ONE EIGHTH BLOCK-2 → 2594 — upper one eighth block
1FB77	—	HORIZONTAL ONE EIGHTH BLOCK-3
1FB78	—	HORIZONTAL ONE EIGHTH BLOCK-4
1FB79	—	HORIZONTAL ONE EIGHTH BLOCK-5
1FB7A	—	HORIZONTAL ONE EIGHTH BLOCK-6
1FB7B	—	HORIZONTAL ONE EIGHTH BLOCK-7 → 2581 — lower one eighth block
1FB7C	┌	LEFT AND LOWER ONE EIGHTH BLOCK
1FB7D	┐	LEFT AND UPPER ONE EIGHTH BLOCK
1FB7E	└	RIGHT AND UPPER ONE EIGHTH BLOCK

1FB7F	┘	RIGHT AND LOWER ONE EIGHTH BLOCK
1FB80	└	UPPER AND LOWER ONE EIGHTH BLOCK

Window title bar

This character is a legacy graphic used to draw the title bar of the active window. The lines corresponding to 3 and 5 are not actually block elements, but can show any horizontally repeating pattern.

1FB81	≡	HORIZONTAL ONE EIGHTH BLOCK-1358
-------	---	----------------------------------

Block elements

1FB82	■	UPPER ONE QUARTER BLOCK → 2582 ■ lower one quarter block
1FB83	■	UPPER THREE EIGHTHS BLOCK → 2583 ■ lower three eighths block
1FB84	■	UPPER FIVE EIGHTHS BLOCK → 2585 ■ lower five eighths block
1FB85	■	UPPER THREE QUARTERS BLOCK → 2586 ■ lower three quarters block
1FB86	■	UPPER SEVEN EIGHTHS BLOCK → 2587 ■ lower seven eighths block
1FB87	▮	RIGHT ONE QUARTER BLOCK → 258E ▮ left one quarter block
1FB88	▮	RIGHT THREE EIGHTHS BLOCK → 258D ▮ left three eighths block
1FB89	▮	RIGHT FIVE EIGHTHS BLOCK → 258B ▮ left five eighths block
1FB8A	▮	RIGHT THREE QUARTERS BLOCK → 258A ▮ left three quarters block
1FB8B	▮	RIGHT SEVEN EIGHTHS BLOCK → 2589 ▮ left seven eighths block

Rectangular shade characters

1FB8C	▒	LEFT HALF MEDIUM SHADE
1FB8D	▒	RIGHT HALF MEDIUM SHADE
1FB8E	▒	UPPER HALF MEDIUM SHADE
1FB8F	▒	LOWER HALF MEDIUM SHADE
1FB90	▒	INVERSE MEDIUM SHADE → 2592 ▒ medium shade
1FB91	▒	UPPER HALF BLOCK AND LOWER HALF INVERSE MEDIUM SHADE
1FB92	▒	UPPER HALF INVERSE MEDIUM SHADE AND LOWER HALF BLOCK
1FB93	▒	<reserved>
1FB94	▒	LEFT HALF INVERSE MEDIUM SHADE AND RIGHT HALF BLOCK

Fill characters

1FB95	▣	CHECKER BOARD FILL → 259A ▣ quadrant upper left and lower right → 1F67F ▣ reverse checker board
1FB96	▣	INVERSE CHECKER BOARD FILL → 259E ▣ quadrant upper right and lower left → 1F67E ▣ checker board
1FB97	≡	HEAVY HORIZONTAL FILL • upper middle and lower one quarter block → 3013 ≡ geta mark → 1CDB7 ≡ block octant-3478

Diagonal fill characters

The filled area for these diagonal fill characters typically covers between one quarter and one half the total area. The diagonal lines should be of uniform width.

- 1FB98 UPPER LEFT TO LOWER RIGHT FILL
→ 25A7 square with upper left to lower right fill
- 1FB99 UPPER RIGHT TO LOWER LEFT FILL
→ 25A8 square with upper right to lower left fill

Smooth mosaic terminal graphic characters

- 1FB9A UPPER AND LOWER TRIANGULAR HALF BLOCK
→ 29D7 black hourglass
- 1FB9B LEFT AND RIGHT TRIANGULAR HALF BLOCK
→ 29D3 black bowtie

Triangular shade characters

- 1FB9C UPPER LEFT TRIANGULAR MEDIUM SHADE
→ 25E4 black upper left triangle
- 1FB9D UPPER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E5 black upper right triangle
- 1FB9E LOWER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E2 black lower right triangle
- 1FB9F LOWER LEFT TRIANGULAR MEDIUM SHADE
→ 25E3 black lower left triangle

Character cell diagonals

- 1FBA0 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT
- 1FBA1 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT
- 1FBA2 BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE
- 1FBA3 BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBA4 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBA5 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBA6 BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBA7 BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT
- 1FBA8 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT AND MIDDLE RIGHT TO LOWER CENTRE
- 1FBA9 BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT AND MIDDLE LEFT TO LOWER CENTRE
- 1FBAA BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE TO MIDDLE LEFT
- 1FBAB BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBAC BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBAD BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBAE BOX DRAWINGS LIGHT DIAGONAL DIAMOND
→ 25C7 white diamond

Light solid line with stroke

- 1FBAF BOX DRAWINGS LIGHT HORIZONTAL WITH VERTICAL STROKE
→ 2500 box drawings light horizontal

Terminal graphic characters

- 1FBB0 ARROWHEAD-SHAPED POINTER
→ 27A4 black rightwards arrowhead
- 1FBB1 INVERSE CHECK MARK
→ 2713 check mark
- 1FBB2 LEFT HALF RUNNING MAN
• paired with 1FBB3 , faces to the right
• the Apple II documentation refers to these characters as “Running Man”
→ 1F3C3 runner
- 1FBB3 RIGHT HALF RUNNING MAN

Arrows

- 1FBB4 INVERSE DOWNWARDS ARROW WITH TIP LEFTWARDS
→ 21B2 downwards arrow with tip leftwards
→ 21B5 downwards arrow with corner leftwards
- 1FBB5 LEFTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB6 RIGHTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB7 DOWNWARDS ARROW AND RIGHT ONE EIGHTH BLOCK
- 1FBB8 UPWARDS ARROW AND RIGHT ONE EIGHTH BLOCK

Terminal graphic characters

- 1FBB9 LEFT HALF FOLDER
• paired with 1FBBA
→ 1F4C1 file folder
→ 1F5C0 folder
- 1FBBA RIGHT HALF FOLDER
- 1FBBB VOIDED GREEK CROSS
→ 0023 number sign
→ 256C box drawings double vertical and horizontal
→ 2719 outlined greek cross
→ 271A heavy greek cross
→ 1F7A3 medium greek cross
- 1FBBC RIGHT OPEN SQUARED DOT
→ 22A1 squared dot operator

Negative terminal graphic characters

The glyphs for these “negative” characters do not necessarily extend to the edges of the character cell.

- 1FBBD NEGATIVE DIAGONAL CROSS
• diagonals extend past the corners of the box, unlike in 274E
→ 2573 box drawings light diagonal cross
→ 274E negative squared cross mark
- 1FBBE NEGATIVE DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBBF NEGATIVE DIAGONAL DIAMOND

Terminal graphic characters

- 1FBC0 WHITE HEAVY SALTIRE WITH ROUNDED CORNERS
→ 274C cross mark
→ 1F5D9 cancellation x
→ 1F7AC heavy saltire

- 1FBC1  LEFT THIRD WHITE RIGHT POINTING INDEX
 • glyph part, combined with 1FBC2  and 1FBC3 
 → 261E  white right pointing index
- 1FBC2  MIDDLE THIRD WHITE RIGHT POINTING INDEX
- 1FBC3  RIGHT THIRD WHITE RIGHT POINTING INDEX
- 1FBC4  NEGATIVE SQUARED QUESTION MARK
 • glyph does not necessarily extend to the edges of the character cell
 → 003F ? question mark
 → 2BD1  uncertainty sign
 → FFFD  replacement character
- 1FBC5  STICK FIGURE
 → 1F6B9  mens symbol
- 1FBC6  STICK FIGURE WITH ARMS RAISED
- 1FBC7  STICK FIGURE LEANING LEFT
- 1FBC8  STICK FIGURE LEANING RIGHT
- 1FBC9  STICK FIGURE WITH DRESS
 → 1F6BA  womens symbol
- 1FBCA  WHITE UP-POINTING CHEVRON
 → 21E7  upwards white arrow
 → 2302  house
 → 1F835  upwards finger-post arrow

Terminal graphic characters

- 1FBCB  WHITE CROSS MARK
- 1FBCC  RAISED SMALL LEFT SQUARE BRACKET
- 1FBCE  BLACK SMALL UP-POINTING CHEVRON

Block elements

- 1FBCE  LEFT TWO THIRDS BLOCK
- 1FBCF  LEFT ONE THIRD BLOCK

Character cell diagonals

- 1FBD0  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER LEFT
- 1FBD1  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT
- 1FBD2  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT
- 1FBD3  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER RIGHT
- 1FBD4  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE
- 1FBD5  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER RIGHT
- 1FBD6  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO LOWER CENTRE
- 1FBD7  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER LEFT
- 1FBD8  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO UPPER RIGHT
- 1FBD9  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE CENTRE TO LOWER RIGHT
- 1FBDA  BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO MIDDLE CENTRE TO LOWER RIGHT
- 1FBDB  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO LOWER LEFT
- 1FBDC  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE TO UPPER RIGHT
- 1FBDD  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT TO LOWER RIGHT
- 1FBDE  BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO UPPER CENTRE TO LOWER RIGHT
- 1FBDF  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT TO LOWER LEFT

Geometric shapes

- 1FBE0  TOP JUSTIFIED LOWER HALF WHITE CIRCLE
- 1FBE1  RIGHT JUSTIFIED LEFT HALF WHITE CIRCLE
- 1FBE2  BOTTOM JUSTIFIED UPPER HALF WHITE CIRCLE
- 1FBE3  LEFT JUSTIFIED RIGHT HALF WHITE CIRCLE
- 1FBE4  UPPER CENTRE ONE QUARTER BLOCK
- 1FBE5  LOWER CENTRE ONE QUARTER BLOCK
- 1FBE6  MIDDLE LEFT ONE QUARTER BLOCK
- 1FBE7  MIDDLE RIGHT ONE QUARTER BLOCK
- 1FBE8  TOP JUSTIFIED LOWER HALF BLACK CIRCLE
- 1FBE9  RIGHT JUSTIFIED LEFT HALF BLACK CIRCLE
- 1FBEA  BOTTOM JUSTIFIED UPPER HALF BLACK CIRCLE
- 1FBEB  LEFT JUSTIFIED RIGHT HALF BLACK CIRCLE
- 1FBECE  TOP RIGHT JUSTIFIED LOWER LEFT QUARTER BLACK CIRCLE
- 1FBED  BOTTOM LEFT JUSTIFIED UPPER RIGHT QUARTER BLACK CIRCLE
- 1FBEE  BOTTOM RIGHT JUSTIFIED UPPER LEFT QUARTER BLACK CIRCLE
- 1FBEF  TOP LEFT JUSTIFIED LOWER RIGHT QUARTER BLACK CIRCLE

Segmented digits

- 1FBF0  SEGMENTED DIGIT ZERO
 ≈ 0030 0 digit zero
- 1FBF1  SEGMENTED DIGIT ONE
 ≈ 0031 1 digit one
- 1FBF2  SEGMENTED DIGIT TWO
 ≈ 0032 2 digit two
- 1FBF3  SEGMENTED DIGIT THREE
 ≈ 0033 3 digit three
- 1FBF4  SEGMENTED DIGIT FOUR
 ≈ 0034 4 digit four
- 1FBF5  SEGMENTED DIGIT FIVE
 ≈ 0035 5 digit five
- 1FBF6  SEGMENTED DIGIT SIX
 ≈ 0036 6 digit six
- 1FBF7  SEGMENTED DIGIT SEVEN
 ≈ 0037 7 digit seven
- 1FBF8  SEGMENTED DIGIT EIGHT
 ≈ 0038 8 digit eight
- 1FBF9  SEGMENTED DIGIT NINE
 ≈ 0039 9 digit nine

Terminal graphic character

- 1FBFA  ALARM BELL SYMBOL
 → 237E  bell symbol
 → 1F514  bell